

## Enclosed Full Voltage Non-Reversing Starters

Max. Horsepower Ratings						Auxiliary Contacts On Each Contactor		Current Rating of Contactor	Catalog Number	Catalog Number
Single-Phase		Three-Phase							Type 1	Type 12/3R
115 V	230 V	200 V	230 V	460 V	575 V	N.O.	N.C.			
1/3	1	2	2	5	7.5	1	1	9	LE1D093A82.....	LE1D093A72.....
1/2	2	3	3	7.5	10	1	1	12	LE1D123A82.....	LE1D123A72.....
1	3	5	5	10	15	1	1	18	LE1D183A82.....	LE1D183A72.....
2	3	5	7.5	15	20	1	1	25	LE1D253A82.....	LE1D253A72.....
2	5	7.5	10	20	25	1	1	32	LE1D323A82.....	LE1D323A72.....
3	5	10	10	30	30	1	1	40	LE1D403A82.....	LE1D403A72.....
3	7.5	12	15	40	40	1	1	50	LE1D503A82.....	LE1D503A72.....
5	10	20	20	40	50	1	1	65	LE1D653A82.....	LE1D653A72.....
7.5	15	30	30	60	60	1	1	80	LE1D803A82.....	LE1D803A72.....

## Enclosed Full Voltage Reversing Starters

Max. Horsepower Ratings						Auxiliary Contacts On Each Contactor		Current Rating of Contactor	Catalog Number	Catalog Number
Single-Phase		Three-Phase							Type 1	Type 12/3R
115 V	230 V	200 V	230 V	460 V	575 V	N.O.	N.C.			
1/3	1	2	2	5	7.5	1	1	9	LE2D093A82.....	LE2D093A72.....
1/2	2	3	3	7.5	10	1	1	12	LE2D123A82.....	LE2D123A72.....
1	3	5	5	10	15	1	1	18	LE2D183A82.....	LE2D183A72.....
2	3	5	7.5	15	20	1	1	25	LE2D253A82.....	LE2D253A72.....
2	5	7.5	10	20	25	1	1	32	LE2D323A82.....	LE2D323A72.....
3	5	10	10	30	30	1	1	40	LE2D403A82.....	LE2D403A72.....
3	7.5	12	15	40	40	1	1	50	LE2D503A82.....	LE2D503A72.....
5	10	20	20	40	50	1	1	65	LE2D653A82.....	LE2D653A72.....
7.5	15	30	30	60	60	1	1	80	LE2D803A82.....	LE2D803A72.....